

Driver Compatibility Table for Skylark SL NEO Software

Matrox DSX Utils

Driver	Build	From version	To version	Note
Matrox DSX Utils 9.8-sp2	9.8.2.22465	2.3.8	Current versions	Identical to 9.8-sp1. Fixed: incorrect temperature definition and displaying the corresponding warning.
Matrox DSX Utils 9.8-sp1	9.8.1.22400	2.3.8	Current versions	
Matrox DSX Utils 9.7	9.7.0.21679	2.0.171	2.3.7	Including all 2.1.x and 2.2.x versions
Matrox DSX Utils 9.7 b2	-	2.0.123-dsx-9.7b2	-	Only for the 2.0.123-dsx-9.7b2 version (10.04.2016)
Matrox DSX Utils 9.5-sp1	9.5.1.17803	2.0.69	2.0.170	
Matrox DSX Utils 9.6	9.6.0.18832	2.0.67	2.0.69	Work stability somewhat depends on positioning of graphic cards in motherboard sockets. There are some problems with PAL flash frames at the output.
Matrox DSX Utils 9.5 b3	9.5.0.17424	2.0.6	2.0.64	
Matrox DSX Utils 9.3	9.3.0.5243	1.7.116	2.0.5	
Matrox DSX Utils 9.2 SP2	9.2.2.2317	1.7.56	1.7.115	Does not work with old PCI-X boards
Matrox DSX Utils 9.1	9.1.0.794	1.5.0	1.7.55	
Matrox DSX Utils 7.5 SP1		1.2.x	1.4.x	

BlackMagic Desktop Video

Driver	Software version	Note
Desktop Video 10.11.2	From the 2.4.24 version	
Desktop Video 10.9.7	Compatible with the 2.3 line	For Duo2 and Quad2 boards
Desktop Video 10.9.3	Compatible with the 2.2 line	
Desktop Video 10.4.2	Compatible with 1.7, 1.8, 1.9, 2.0, 2.1 lines	
Desktop Video 10.3.2	unknown-1.9.89-unknown	
Desktop Video 9.8	unknown-unknown	
Desktop Video 9.6.5	unknown-unknown	

StreamLabs MH4LM or MH4L

Driver	Software version	Note
The SLDriversSetup-2.0.14.224.exe driver with e21a_MH4LM_w_VBI_pcb14.pof board firmware (no signature).	1.9, 2.0, 2.1, 2.2	Skylark software works only with boards on Altera30 chipsets.
The signed 1.1.12.1 driver of 13.12.2017 under Win10 with e21a_MH4LM_w_VBI_pcb14.pof (with a signature, 2097440 byte) or 45 board firmware. Used SDK-StreamLabsSDKAndTools_2.1.625.30123_20180209. Hardware revision of boards v1.5.	2.3.87-	Skylark software works only with boards on Altera30 chipsets.

StreamLabs MS416

Driver	Software version	Note
2.0.13.719 with the MS416_v11_16072012.pof board firmware	1.9, 2.0, 2.1	

From:

<https://wiki.skylark.tv/> - **wiki.skylark.tv**

Permanent link:

https://wiki.skylark.tv/hardware/driver_compatibility_table

Last update: **2019/10/30 05:41**

